



iCafeCard Manager Software Administrator Log On



iCafe Manager Software Log On

After you install the iCafe Manager Software onto your Administrator PC this log on window will appear, prompting you to enter in your username and password to access the software.

The iCafe Manager Software

The iCafe Manager Software is used to set your System Configurations and to load the iCafe cards. The Configurations and iCafe cards are set up in the Management Console in four steps.

- (1) **Client Configuration** (input usernames, passwords, and standard card settings)
- (2) **Card Management** (card status, card loading)
- (3) **Client Messages** (create customized client text messages)
- (4) **Settings** (loyalty and demographic message and settings)



iCafeCard Manager Software Management Console

(1) Client Configuration

This screen is used to set up the usernames, passwords, and other global settings for all of the iCafe cards that you will create.

Client Log On Information—to set up a username, password, user type and location ID to be loaded onto the iCafe cards.

The screenshot shows the 'Client Configuration' tab in the iCafe Management Console. It includes an 'Instructions' section, a 'Client Log On Information' section with fields for Username (icafe user), Password, Re-type password, Client authentication method (Log users onto local machine selected), Domain Name, User Type (Guests), and Location Number (01). There are 'Save' and 'Close' buttons at the bottom.

(2) Card Management

This screen is used to read and recharge the iCafe cards.

Card Status—to read the data on the iCafe cards.

Card Reload (*cmbCardLoadDay*)—to set the amount of time to be loaded onto the iCafe cards (Choose from minutes/hours or days).

The screenshot shows the 'Card Management' tab in the iCafe Management Console. It includes an 'Instructions' section, a 'Card Status' section with fields for Card ID, Time currently on card, and Email address, and a 'cmbCardLoadDay' section with dropdowns for Minutes/Hours (1hr, 60min) and Days (N/A), a checkbox for 'Reload unlimited use', and buttons for 'Add Time', 'Reset/Reload Card', 'Auto Reload', 'Load Default Time', and 'Save Default Time'. There is a 'Read Card Data' button and a 'Close' button at the bottom.



iCafeCard Manager Software Management Console

The screenshot shows the 'iCafe Management Console' window with the 'Client Messages' tab selected. It contains an 'Instructions' section and three text input fields for 'Log On Message', 'Log Off Message', and 'Welcome Message'. The fields contain the text 'log on', 'log off', and 'welcome' respectively. At the bottom, there are buttons for 'Use Default Messages', 'Clear', 'Save', and 'Close'.

(3) Client Messages

The client message set-up enables you to enter messages that will display on the client PC's informing and instructing your customers about your establishment and how to use the iCafe system.

Log On Message—what the customer sees before inserting the iCafe card.

Log Off Message—what the customer sees when time has expired on the iCafe card.

Welcome Message—what the customer sees when logged onto the PC.

The screenshot shows the 'iCafe Management Console' window with the 'Settings' tab selected. It contains an 'Instructions' section, a 'Loyalty' section with checkboxes and dropdowns for 'Activate Loyalty' and 'Loyalty Bonus Configuration', and a 'User Demographic Information' section with a checkbox for 'Activate Demographic Tracking Only' and a text field for 'Demographic/Loyalty message'. At the bottom, there are buttons for 'Show Demographic Default', 'Show Loyalty Default', 'Clear', 'Save', and 'Close'.

(4) Settings

The Loyalty/Demographic features allow you to collect customer information as well as assign loyalty points to reward frequent customers.

Loyalty—tracks the amount of time a customer has spent logged onto the iCafe system.

User Demographic Information—collects customer information.